Acoustic Calibrator - Class 2, 114 dB



Features

- IEC 60942:2003 Class 2
- ANSI S1.40:2006
- Sound pressure level 114 dB
- Frequency 1 kHz
- Fits ½" microphones

Applications

- Calibration of noise dosimeters
- Calibration check of noise at work meter
- Field calibration checks
- Required by many noise regulations

Overview

The CR518 Acoustic Calibrator meets ANSI S1.40:2006 and IEC 60942:2003 to Class 2. It is intended for use with noise dosimeters and noise at work meters that may require the higher calibration level.

This calibrator is included with the doseBadge Professional range of noise dosimeter kits, along with the doseBadges, charger, carrying case and software.

Using It

As soon as the calibrator is switched on it emits a 1 kHz tone at 114 dB. The calibrator should be pushed carefully (firmly, but slowly) on to the microphone.

The meter should now be adjusted accordingly. There will often be a free-field adjustment to make for the microphone in use. So, for example, you may actually be adjusting to 113.8 dB on the meter. Meters like the doseBadge Pro make these adjustments automatically and deal with any corrections needed.

NoiseMeters

Acoustic Calibrator - Class 2, 114 dB

Specifications

Standards IEC 60942:2003 Class 2

ANSI S1.40:2006

Sound Level 114.0 dB \pm 0.4 dB

Frequency 1 kHz ± 1%

Distortion < 2%

Reference 23°C, 101.3 kPa, 65% RH

conditions

Microphone ½" (to IEC 1094-4)

size

Battery type 1 x 9v (PP3, 6LR61, 6F22)

Dimensions 121 x Ø47 mm Weight 220 g with battery

Controls Push button start, Automatic

switch off with green

LED indication. User override

of automatic switch off

CE EN 61000-6-3:2007+A1:2011

classification

EN 61000-6-1:2007

Head Office

NoiseMeters Ltd 7 Jayes Park Ockley Surrey RH5 5RR

Telephone **0845 680 0312** Fax **0845 680 0316**

Email: info@noisemeters.co.uk Support: support@noisemeters.co.uk

Web Sites

Main site:

https://www.noisemeters.co.uk

Product shortcut:

https://www.noisemeters.co.uk/product/cr/calibrator/cr518/

Tech Support:

https://support.noisemeters.com