Acoustic Calibrator - Class 1



Features

- IEC 60942:2003 Class 1
- ANSI S1.40:2006
- Sound pressure level 94 dB
- Frequency 1 kHz
- Fits ½" microphones
- Adapter available for ¼" microphones

Applications

- Calibration check of Class 1 sound level meter
- Field calibration checks
- Calibration of environmental noise monitors
- Required by many noise regulations

Overview

The CR515 Acoustic Calibrator meets ANSI S1.40:2006 and IEC 60942:2003 to Class 1, the more accurate grade. It is most suited to the Class 1 sound level meters and environmental noise monitors that NoiseMeters offers.

This calibrator is included in most of the Class 1 Noise Measurement Kits and Outdoor Noise Kits, along with the sound level meter, carrying case and software where applicable. Please refer to the sound level meter web pages for more information.

Using It

As soon as the calibrator is switched on it emits a 1 kHz tone at 94 dB. The calibrator should be pushed carefully (firmly, but slowly) on to the microphone capsule.

The meter should now be adjusted accordingly. There will often be a free-field adjustment to make for the microphone in use. So, for example, you may actually be adjusting to 93.8 dB on the meter. For meters provided by NoiseMeters this is either dealt with automatically by the meter, or is covered in the meter's User Manual.

NoiseMeters

Acoustic Calibrator - Class 1

Specifications

Standards IEC 60942:2003 Class 1

ANSI S1.40:2006

Type Approval PTB-1.61-4028829

LNE-24906

CEM 140786001

Sound Level 94.0 dB \pm 0.2 dB

Frequency 1 kHz ± 1%

Distortion < 2%

Reference 23°C, 101.3 kPa, 65% RH

conditions

Microphone ½" (to IEC 1094-4)

size

Hz ± 1% %

29 0, 101.5 Ki a, 0570 Ki i

adapter Battery type Dimensions Weight

Controls

CE

Calibration

microphone capsules 1 x 9v (PP3, 6LR61, 6F22) 121 x Ø47 mm 220 g with battery

Push button start, Automatic

switch off with green

QD7 for use with 1/4"

LED indication. User override

of automatic switch off

EN 61000-6-3:2007+A1:2011

classification

EN 61000-6-1:2007

Head Office

NoiseMeters Ltd 7 Jayes Park Ockley Surrey RH5 5RR

Telephone **0845 680 0312** Fax **0845 680 0316**

Email: info@noisemeters.co.uk Support: support@noisemeters.co.uk **Web Sites**

Main site:

https://www.noisemeters.co.uk

Product shortcut:

https://www.noisemeters.co.uk/p/cr515/

Tech Support:

https://support.noisemeters.com